

# Cobham AVIATOR HGA-6500

Inmarsat SATCOM High Gain Antenna

**COBHAM**

## Data Sheet

The most important thing we build is trust

### Description

The HGA-6500 is a ruggedized mechanically steered SwiftBroadband, Swift64 and Aero H/H+ SATCOM Antenna. Derived from the successful HGA-6000, the HGA-6500 is specifically designed for external mount on helicopters and slower flying aircraft. The HGA-6500 accepts steering commands directly from any ARINC 741 compatible system. This eliminates the need to install a separate Antenna Control Unit (ACU) or Beam Steering Unit (BSU), reducing system box count, which in turn improves empennage weight distribution and installation simplicity.

### Features

- Smallest swept volume available for a mechanically steered High Gain Antenna
- Higher gain than single helix antenna designs
- Excess gain can be used for longer RF cable runs between antenna and DLNA
- Integral Beam Steering Unit with ARINC 429 interface reduces overall box count
- Ruggedized and qualified for helicopter installation
- Externally mountable with fairing. No additional radome required
- ARINC 741/781 compatible

### Technical Specifications

#### Dimensions

	Stand-Alone	With Adaptor
Length:	256 mm (10")	334 mm (13.13")
Width:	256 mm (10")	290 mm (11.42")
Height:	247 mm (9.70")	258 mm (10.16")
Weight:	1.8 kg (3.96lbs)	3.8 kg (8.38 lbs)

#### Interfaces

RF:	TNC Male (Stand-Alone + Adapter)
Control:	Multi-pin or MXC Female (Stand-Alone) ARINC 741 or SMA Female (Adapter)

#### Altitude

70,000 ft

#### Temperature Range

-65 to +70 deg C

#### Voltage

28 Vdc

#### Power

22.4 W

#### Qualification

DO-160E

For further information, please contact:

Cobham SATCOM, Cape Town

Tel: +27 21 700 7000

Fax: +27 21 700 7199

Email: [satcom.capetowninfo@cobham.com](mailto:satcom.capetowninfo@cobham.com)

or:

Distributed By:

